



TEST REPORT
IEC 60269-1: 2006/A2: 2014
Low-voltage fuses
Part 1: General requirements
IEC 60269-2:2016
Semiconductor devices -
Part 2: Discrete devices - Rectifier diodes

Report

Reference No.: JDT2021KD047-LVD

Compiled by (+ signature): *Tom Zhu*Reviewed by (+ signature): *Evan Wang*Approved by (+ signature): *duke mao*

Contents: 33

Date of issue: May. 31, 2021

Testing laboratory

Name: Shenzhen Jiace Detection Technology Co., Ltd.

Address: No. 9, Shunda Industrial Park, Guangming New District, Shenzhen,
Guangdong, China

Testing location: As above

Client

Name: HIMEL HONG KONG LIMITED

Address: 11/F KERRY CTR 683 KING'S RD
QUARRY BAY – Hong Kong**Manufacturer**

Name: DELIXI GROUP CO., LTD.

Address: No. 155 East Zhandong Road, Dianhou village, Liushi town,
Yueqing City, Zhejiang Province, China.**Test specification**

Standard: IEC 60269-1 : 2006+A1:2009+A2 : 2014, IEC 60269-2:2016

Test procedure: LVD (2014/35/EU)

Procedure deviation: N.A.

Non-standard test method: N.A.

Test Report Form/blank test report

Test Report Form No.: 60269 D/01-08

TRF originator: JDT/ITD/KD

Master TRF: reference No. 60269 D, dated 01

Test item Description : FUSE Trademark..... :/ Test model and/or type reference..... : HRT18-125/ ϕ 22 \times 58 125A Ratings.....: 500V~1250A 50Hz
Particulars: test item vs. test requirements Equipment mobility..... : Stationary Operating condition : Continuous IT testing, phase-phase voltage (V) : N.A. Class of equipment : Class I
Test case verdicts Test case does not apply to the test object..... : N(A.) Test item does meet the requirement : P(ass) Test item does not meet the requirement : F(ail)
Testing Date of receipt of test item : May.31, 2021 Date(s) of performance of test..... : May. 06, 2021 to May. 31, 2021
General remarks This test report shall not be reproduced except in full without the written approval of the testing laboratory. The test results presented in this report relate only to the item tested. "(see remark #)" refers to a remark appended to the report. "(see appended table)" refers to a table appended to the report. Throughout this report a comma is used as the decimal separator.
Brief description of the tested sample(s) Ambient temperature: 25°C humidity: 55% Complete test was conducted on HRT18-125/ ϕ 22 \times 58 125A , HRT18-32(X)/ ϕ 10 \times 38, HRT18-63(X) / ϕ 14 \times 51, HRT18-125(X)/ ϕ 22 \times 58.

Summary of testing:

Survey of tests on fuse-links and number of fuse-links to be tested

[illegible]

Survey of tests on fuse-links and number of fuse-links to be tested

[illegible]

[illegible]

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
5	CHARACTERISTICS OF FUSES		
5.2	Rated voltage (V) as specified	AC500V	P
5.3.1	Rated current (A) of the fuse-link in accordance with specified values	125A	P
5.3.2	Rated current (A) of the fuse-holder	125A	P
5.4	Rated frequency (Hz)		N/A
5.5	Max. rated power dissipation (VA) of fuse-link	See IEC 60269-2	N/A
	Rated acceptable power dissipation (VA) of fuse-holder	See IEC 60269-2	N/A
5.6	Limits of time-current characteristics based on reference ambient air temperature Ta of +20°C		
5.6.1	Time-current zones deviated from standardized, or available in manufacturers documentation (with tolerances)	Figure 4 of IEC 60269-2	P
5.6.2	Conventional times and currents see Table 2	Table 2 of IEC 60269-1 Table 101 of IEC 60269-2	P
5.6.3	Gates.....	Table 3 of IEC 60269-1 Table 102 of IEC 60269-2	P
5.7	Breaking range and breaking capacity		
5.7.1	Breaking range and utilization category.....	gG	P
5.7.2	Rated breaking capacity (A) of fuse-link corresponds to the rated voltage (V), and is equal or higher than given minimum (A) in subsequent part of this standard	AC500V 100kA	P
5.8	Cut-off current and I^2t characteristics are referred to the values of voltage, frequency and power factor		
5.8.1	Cut-off current characteristics, if required, given by the manufacturer according to Figure 4		P
5.8.2	Pre-arcing I^2t characteristics for pre-arcing times of less than 0,1 s down to a time corresponding to the rated breaking capacity given by the manufacturer :		P
	The operating I^2t characteristics with specified voltages as parameter for pre-arcing times less than 0,1 s given by the manufacturer		P
6	MARKINGS		
	Markings are durable and easily legible		P
6.1	Fuse-holders marked by:		
	- name of manufacturer or trade mark which enable identification of fuse-holder		P
	- manufacturer's identification reference enabling to find all characteristics listed in 5.1.1		P
	- rated voltage (V)	AC500V	P
	- rated current (A)	125A	P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	- kind of current and rated frequency (Hz)	AC	P
6.2	Fuse-link(s) except small fuse-link(s) marked by:		
	- name of manufacturer or trade mark which enable identification of fuse-links.....		P
	- manufacturer's identification reference enabling to find all characteristics listed in 5.1.2		P
	- rated voltage (V)	AC500V	P
	- rated current (A)	125A	P
	- breaking range and utilization category (if applicable) (5.7.1)	gG	P
	- kind of current	AC	P
	- rated frequency (Hz), if applicable (5.4)		N/A
	Small fuse-links marked by:		
	- trademark		N/A
	- list reference of manufacturer		N/A
	- rated voltage (V)		N/A
	- rated current (A)		N/A
6.3	Symbols for the kind of current and frequency in accordance with EN 60417		P
7	STANDARD CONDITIONS FOR CONSTRUCTION		
7.1	Mechanical design		
7.1.1	Replacement of fuse-links easily and safely		P
7.1.2	Connections, including terminals		
	Contact force is not transmitted through insulating material other than ceramic or other material with characteristics not less suitable, unless		P
	there is sufficient resilience in the metallic parts to compensate any possible shrinkage or other deformation of the insulating material		P
	Terminals cannot turn or be displaced when the connecting screws are tightened		P
	Terminals shall be such, that the conductors cannot be displaced		P
	Parts gripping the conductors are of metal		P
	Gripping parts cannot unduly damage conductors		P
	Terminals readily accessible under the intended conditions of installation		P
7.1.3	Fuse-contacts		
	Fuse-contacts are such that necessary contact force is maintained under the conditions of service and operation		P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	Contact is such that electromagnetic forces occurring during operation under conditions in accordance with 7.5 not impair electrical connections between		
	a) fuse-base and fuse-carrier		N/A
	b) fuse-carrier and fuse-link		N/A
	c) fuse-link and fuse-base		P
	Fuse contacts are so constructed and of such material that, when fuse is properly installed and service conditions are normal, adequate contact is maintained		
	a) after repeated engagement and disengagement		P
	b) after being left undisturbed in service for long period		P
7.1.4	Construction of a gauge-pENe		
	Gauge-pENe is so designed that it withstands normal stresses occurring during use		P
7.1.5	Mechanical strength of fuse-link		
	Fuse-link have adequate mechanical strength and its contacts are securely fixed		P
7.2	Insulating properties and suitability for isolation		
	Fuses are such that they do not lose insulating properties at voltages to which they are subjected in normal service		P
	Fuse passes the tests for verification of insulating properties and suitability for isolation in accordance with 8.2		P
7.3	Temperature rise, power dissipation of the fuse-link and acceptable power dissipation of the fuse-holder		
	See Table 5 :		P
	Requirements are verified by tests according to 8.3		P
7.4	Operation		
	Fuse-link is so designed and proportioned that, when tested in its appropriate test arrangement at rated frequency and ambient air temperature of (20±5)°C		P
	- is able to carry continuously any current not exceeding its rated current		P
	- is able to withstand overload conditions as they may occur in normal service (see 8.4.3.4)		P
	Fuse-link satisfy these conditions if it passes the tests prescribed in 8.4		P
7.5	Breaking capacity		

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	Fuse is capable of breaking, at rated frequency and at voltage not exceeding the recovery voltage specified in 8.5, any circuit having prospective current between		P
	- current I_f (for "g" fuse-links)		P
	- current $k_2 I_n$ (for "a" fuse-links)		N/A
	- for a.c., rated breaking capacity at power factors not lower than those in Table 20		P
	- for d.c., rated breaking capacity at time constants not greater than those limits in Table 21		P
	Arc voltage not exceed values given in Table 6		P
	Fuse satisfy these conditions if it passes the tests prescribed in 8.5		P
7.6	Cut-off current characteristic		
	Values of cut-off current measured as specified in 8.6 are less than, or equal to, the values corresponding to cut-off current characteristics assigned by the manufacturer		P
7.7	I^2t characteristics		
	Pre-arcing I^2t values verified according to 8.7 (Table 7)		P
	Operating I^2t values verified according to 8.7		P
7.8	Overcurrent discrimination of fuse-links		P
7.9	Protection against electric shock		
	The degree of protection when the fuse is under normal service conditions:	IP20	P
	The degree of protection when replacing the fuse-link:	IP20	P
	The degree of protection when the fuse-link and fuse-carrier is removed:	IP20	P
7.9.1	Clearances and creepage distances		
	Clearances are not less than the values given in Table 9		P
	Creepage distances correspond to material group, as defined in 2.7.1.3 of EN 60664-1, corresponding with rated voltage given in Table 10		P
7.9.2	Leakage currents of equipment suitable for isolation		
	Value of leakage current (mA) not exceed		
	- 0,5 mA per pole for fuses in new conditions		P
	- 2 mA per pole for fuses having been submitted to test according to 8.5		P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
7.9.3	Additional constructional requirements for fuses with non-separable fuse-carriers, suitable for isolation		N/A
	Fuse-holder are marked with the symbol EN 60617-S00369		N/A
	When fuse is in open position, with fuse-link remaining inside the fuse-carrier, isolating distance between the fuse contacts in accordance with the isolating function are provided		N/A
	Indication of this position is provided by the position of the fuse-carrier		N/A
	There exists a locking means in order to lock the fuses in the isolated position, locking is possible only in this position		N/A
	Fuses are designed so that the fuse-carrier remains attached to the fuse-base giving correct indication of the open position, and of locking		N/A
7.10	Resistance to heat		
	All components are sufficiently resistant to heat which may occur in normal use (see 8.9 and 8.10)		P
7.11	Mechanical strength		
	All components of fuse are sufficiently resistant to mechanical stresses which may occur in normal use (see 8.3 to 8.5 and 8.11.1)		P
7.12	Resistance to corrosion		
	All metallic components of fuse are resistant to corrosive influences which may occur in normal use		P
7.12.1	Resistance to rusting		
	Ferrous components are so protected that they meet relevant tests (see 8.2.4.2 and 8.11.2.3)		P
7.12.2	Resistance to season cracking		
	Current-carrying parts are sufficiently resistant to season cracking (see 8.2.4.2 and 8.11.2.1)		N/A
7.13	Resistance to abnormal heat and fire		
	All components of fuse are sufficiently resistant to abnormal heat and fire (see 8.11.2.2)		P
7.14	Electromagnetic compatibility		
	Fuses within the scope of this standard are not sensitive to normal electromagnetic disturbances		P
	No immunity tests are required		P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict

8	TESTS		
8.1.2	At the beginning of each test, the fuse is approximately at the ambient temperature		P
8.1.3	Tests made on fuses in clean and dry condition		P
8.1.4	Arrangement of the fuse and dimensions		
	Except for degree of protection test (see 8.8), fuse are mounted in free air in draught-free surroundings in the normal operation position and on insulating material of sufficient rigidity		P
	Before tests are started, specified external dimensions are measured and results compared with dimensions specified in the relevant data sheet of the manufacturer or specified in subsequent parts	Part 2 (IEC 60269-2)	P
8.1.5	Testing of fuse-links		
	Fuse-links tested with the kind(s) of current for which they are rated	AC	P
	Fuse-links tested for a.c. with frequency for which they are rated		N/A
8.1.5.1	Complete tests		
	Internal resistance R measured by a current $\leq 0,1 I_n$	(see appended table)	P
	Measuring current (A)	(see appended table)	P
	Ambient air temperature in range of $20 \pm 5 \text{ }^\circ\text{C}$	24°C	P
	The values of resistance	(see appended table)	P
8.1.5.2	Testing of fuse-links of a homogeneous series		
	Fuse-links tested like a homogeneous series	Yes/No	P
	If yes: fuse-links have identical enclosures in form and construction (except of fuse-elements and contacts)		P
	- the same arc-extinguishing medium and same completeness of filling		P
	- fuse-elements of identical materials		P
	- their cross-section of fuse-elements not exceed the cross-section of fuse-links having the highest rated current		P
	- number of fuse-elements do not exceed number of fuse-elements of fuse-links with the highest rated current		P
	- minimum distances between adjacent fuse-elements and between the fuse-elements and the inner surface of the cartridge is not less than those in the fuse-link with the highest rated current		P
	- fuse-links used with a given fuse-holder, or		P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	- fuse-links intended to be used in an arrangement identical for all rated currents of the homogeneous series		P
	- value of RI_n does not exceed the value for the fuse-link with largest rated current of the homogeneous series (R measured as indicated in 8.1.5.1)		P
	the rated breaking capacity of fuse-links not greater than that of the fuse-link with the largest rated current within the homogeneous series		P
	- if not, the fuse-links with greater breaking capacity subjected to tests no. 1 and no. 2		N/A
	The fuse-link having the largest rated current tested completely according to Table 11		P
	The fuse-link having the smallest rated current tested only according to Table 12		P
	The fuse-links between the largest and smallest rated current tested according to Table 13		P
8.1.6	Testing of fuse-holders		
	The fuse-holders are subjected to the tests according to Table 14		P
8.2	Verification of the insulating properties and of the suitability for isolation		
8.2.1	Arrangement of the fuse-holder		
	The fuse-holder fitted with a fuse-links of the largest dimensions for the type of fuse-holder concerned		P
	The fuse-base fixed to a metal plate, unless otherwise specified		P
	Fuse-link is replace while live - surfaces of fuse-link, of device for replacing it or of fuse-carrier, if of insulating material, are provided with metal coverings connected during tests to the frame of the apparatus; if of metal, they are connected direct to the frame		P
8.2.2	Verification of the insulating properties	#1 (fuse-base)	
	Points of application of the test voltage		
	The test voltage is applied between:		
	a) live parts and the frame with the fuse-link and the device for replacing it, or		P
	the fuse-carrier, if any, in position		N/A
	no breakdown of insulation or flashover during 1 min of the applying test voltage		P
	b) the terminals without fuse-link, device for replacing or the fuse-carrier		P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	no breakdown of insulation or flashover during 1 min of the applying test voltage		P
	c) live parts of different polarity in the case of multipole fuse-holder with fuse-links, fuse-carrier(s) or device(s) for replacing the fuse-links		N/A
	no breakdown of insulation or flashover during 1 min of the applying test voltage		N/A
	d) live parts which in the case of a multipole fuse-holder reach different potential after the fuse-link operates (equipped by fuse-carrier or device for replacing without fuse-link)		N/A
	no breakdown of insulation or flashover during 1 min of the applying test voltage		N/A
	The r.m.s. value of test voltage (V) as specified in Table 15	AC690V	P
8.2.2.3.2	Fuse-holder is subjected to humid atmospheric conditions		
	Relative humidity of ambient air (%)	94%	P
	Ambient air temperature (°C)	25°C	P
	Duration of treatment (h)	48h	P
	Insulation resistance is measured between the points prescribed in 8.2.2.1 by applying d.c. voltage of approximately 500 V		
	Points of measuring:		
	a) min. measured value (MΩ)		P
	b) min. measured value (MΩ)		P
	c) min. measured value (MΩ)		N/A
	d) min. measured value (MΩ)		N/A
	The insulation resistance not less than MΩ	≥1MΩ	P
8.2.3	Verification of the suitability for isolation	#1(fuse-base)	
	Clearances larger than values given in Table 9 are verified by dimensional measurement or by voltage test		
	Points of application of the test voltage		
	The test voltage is applied between:		
	- terminals when the fuse-link and device for replacing it, are removed		P
	Test voltage (kV) for verification of the rated impulse withstand voltage is given in Table 16	9,8kV	P
	The 1,2/50 μs impulse voltage applied 5 times for each polarity at intervals of 1 s minimum		P
	no breakdown of insulation or flashover during of the applying test voltage		P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	no disruptive discharge during the test		P
8.2.4.2	Fuse-holder is subjected to humid atmospheric conditions	See 8.2.2.3.2	
	Relative humidity of ambient air (%)		N/A
	Ambient air temperature (°C)		N/A
	Duration of treatment (h)		N/A
	Insulation resistance is measured between the points prescribed in 8.2.2.1 by applying d.c. voltage of approximately 500 V		N/A
	Points of measuring:		
	a) min. measured value (MΩ)		N/A
	b) min. measured value (MΩ)		N/A
	c) min. measured value (MΩ)		N/A
	d) min. measured value (MΩ)		N/A
	The insulation resistance not less than 1 MΩ		N/A
8.3	Verification of temperature rise and power dissipation		
8.3.1	One fuse used for test (unless otherwise stated by the manufacturer) mounted in free air		
	Test performed at an ambient air temperature of (20±5) °C	21°C	P
	Ambient air temperature during the test (°C)	21°C	P
	Cross-sectional area (see Table17) (mm ² or mm x mm).....	70 mm ² x1m	—
	Tightened by torque; torque (Nm)	10 Nm	—
8.3.2	The temperature of the fuse measured by method of measuring	Thermal couple	P
8.3.3	Measurement of the power dissipation of the fuse-link		
	One fuse used for test (unless otherwise stated by the manufacturer) mounted in free air		P
	Test performed at an ambient air temperature of (20±5) °C	21°C	P
	Ambient air temperature during the test (°C)	21°C	P
	Cross-sectional area (see Table17) (mm ² or mm x mm).....	70 mm ² x1m	—
	Tightened by torque; torque (Nm)	10 Nm	—
8.3.4.1	Temperature rise of the fuse-holder	#2(fuse-base)	
	Applied a.c. current (A) for test equal to the rated current of the fuse-holder	125A	P
	Test made with fuse-link (A), or	125A	P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	with a dummy fuse-link specified in subsequent parts	Part 2	P
	Temperature rise limits T for contacts and terminals (Table 5):		
	spring loaded contacts; limit (K)		N/A
	bolted contacts; limit (K)		N/A
	terminals; limit (K) $\leq 65K$	30K (Max.)	P
8.3.4.2	Power dissipation of a fuse-link	#1 (fuse)	
	The test made with a.c. at the current (A) equal to the rated current of the fuse-link	125A	P
	The points of measuring		P
	Measured value of power (W) dissipation in limits (W) specified in subsequent parts	Part 2(IEC 60269-2) 10,3W	P
8.3.5	The acceptable power dissipation (W) of fuse-holder not less than the rated power dissipation of the corresponding fuse-links		P
	After the tests prescribed in 8.3, the insulating parts of the fuse-holders cooled down to ambient temperature withstood the test voltage according to 8.2		P
	No deformation after tests of 8.3		P
8.4	Verification of operation		
8.4.1	The test arrangement as specified in 8.1.4		
	Length (m) of conductors (see 8.3.1).....	1m	P
	their cross-sectional area (mm ²) as specified in Table 17	70 mm ²	P
8.4.2	Ambient air temperature during test within (20±5) °C	21°C	P
8.4.3.1	Verification of conventional non-fusing and fusing current		
	a) the fuse-link subjected to the conventional non-fusing current (I_{nf}) (see Table 2)	(see appended table)	
	the fuse-link did not operate within the conventional time of (h) (Table 2)	(see appended table)	P
	b) the same fuse-link, after cooled down to ambient temperature, subjected to the conventional fusing current (I_f) (see Table 2)	(see appended table)	
	the fuse-link operated within the conventional time of (minutes) (Table 2)	(see appended table)	P
8.4.3.2	Verification of rated current of "g" fuse-links		
	One fuse-link submitted to a pulse test for 100 h	100h	P
	On-period equal to conventional time (h)	(see appended table)	P
	Off-period of 0,1 of the conventional time	(see appended table)	P
	Test current (A) equal to 1,05 of the rated current ..	(see appended table)	P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	After the test, the fuse-link not have changed its characteristics		P
8.4.3.1	a) the fuse-link subjected to the conventional non-fusing current (I_{nf}) (see Table 2)	(see appended table)	—
	the fuse-link did not operate within the conventional time of (h) (Table 2)	(see appended table)	P
8.4.3.3	Verification of time-current characteristics and gates		
8.4.3.3.1	The time-current characteristics verified on the basis of the test according to 8.5		
	Values of pre-arcing and operating times within the time-current zones:		
	- indicated by the manufacturer		N/A
	- specified in subsequent parts	Part 2	N/A
	Verification for smaller current ratings, if only one largest rated current fuse-link is subjected to the test according to 8.5 (in case of homogeneous series):		
	"g" fuse-links (except "gD", "gG" and "gM")		
	Tests made in connection with verification of the gates (see 8.4.3.3.2)		
	Ambient air temperature within $(20 \pm 5) ^\circ\text{C}$		N/A
	rated current I_n (A) of the fuse-link		
	test performed at voltage (V)		
	test 3a) prospective current (A) equal to kI_n ($10 \leq k \leq 20$)		N/A
	pre-arcing time (s)		
	specified pre-arcing time (s) max./min.		N/A
	test 4a) prospective current (A) equal to kI_n ($5 \leq k \leq 8$)		N/A
	pre-arcing time (s)		
	specified pre-arcing time (s) max./min.		N/A
	test 5a) prospective current (A) equal to kI_n ($2,5 \leq k \leq 4$)		N/A
	pre-arcing time (s)		
	specified pre-arcing time (s) max./min.		N/A
	Verification for smaller current ratings, if only one largest rated current fuse-link is subjected to the test according to 8.5 (in case of homogeneous series):		
	"a" fuse-links		N/A
	Ambient air temperature within $(20 \pm 5) ^\circ\text{C}$		N/A
	rated current I_n (A) of the fuse-link		
	test performed at voltage (V)		
	test 3a) prospective current (A) equal to $nk_2 I_n$ ($5 \leq n \leq 8$)		N/A

IEC 60269-1				
Clause	Requirement + Test	Result - Remark		
	pre-arcing time (s)			
	specified pre-arcing time (s) max./min.			N/A
	test 4a) prospective current (A) equal to $nk_2 I_n$ ($2 \leq n \leq 3$)			N/A
	pre-arcing time (s)			
	specified pre-arcing time (s) max./min.			N/A
	test 5a) prospective current (A) equal to $nk_2 I_n$ ($1 \leq n \leq 1,5$)			N/A
	pre-arcing time (s)			
	specified pre-arcing time (s) max./min.			N/A
8.4.3.3.2	Verification of gates			
	"gG" and "gM" fuse-links	"gG"		
	rated current of the fuse-link (A).....	(see appended table)		
	test performed at voltage (V)	(see appended table)		
	a) testing current (A); pre-arcing time (s) higher than 10 s	(see appended table)		
	b) testing current (A); pre-arcing time (s) less than 5 s	(see appended table)		
	c) testing current (A); pre-arcing time (s) higher than 0,1 s.....	(see appended table)		
	d) testing current (A); pre-arcing time (s) less than 0,1 s.....	(see appended table)		
	"aM" fuse-links			N/A
	rated current of the fuse-link (A).....			
	test performed at voltage (V)			
	Cross-sectional area (see Table18) (mm ² or mm x mm).....			
	e) testing current (A); pre-arcing time (s) higher than 60 s			N/A
	f) testing current (A); pre-arcing time (s) less than 60 s			N/A
	g) testing current (A); pre-arcing time (s) higher than 0,2 s.....			N/A
	h) testing current (A); pre-arcing time (s) less than 0,10 s.....			N/A
8.4.3.4	Overload	I _n =125A		
		#14	#15	#16
	The test arrangement is same as that for the temperature rise test (see 8.3.1)			P
	Three fuse-links submitted to 50 pulses having the same duration and test current	50		

IEC 60269-1				
Clause	Requirement + Test	Result - Remark		
	test performed at voltage (V)	AC500V		
	"g" fuse-links:	gG		
	test current (A) equal to 0,8 times the current stated for a pre-arcing time of 5 s	125A		
	duration of each pulse 5 s	5s		
	time (s) interval between pulses equal to 20 % of the conventional time (s) specified in Table 2	1440s		
	"a" fuse-links:			
	rated current I_n (A) of fuse-link			
	test current (A) equal to $k_1 I_n \pm 2\%$			
	the pulse duration (s) corresponds to that indicated on the overload curve for $k_1 I_n$ stated by manufacturer			
	time (s) intervals between pulses equal to 30 times the pulse duration			
	fuse-links having ambient air temperature subjected to a current (A) equal to current for the overload test	125A		
	pre-arcing time (s) of sample lies within the manufacturers time-current zone	29s	33s	37s
8.4.3.4	Overload	$I_n=32A$		
		#36	#37	#38
	The test arrangement is same as that for the temperature rise test (see 8.3.1)			
	Three fuse-links submitted to 50 pulses having the same duration and test current	50		
	test performed at voltage (V)	AC500V		
	"g" fuse-links:	gG		
	test current (A) equal to 0,8 times the current stated for a pre-arcing time of 5 s	12A		
	duration of each pulse 5 s	5s		
	time (s) interval between pulses equal to 20 % of the conventional time (s) specified in Table 2	720s		
	"a" fuse-links:			
	rated current I_n (A) of fuse-link			
	test current (A) equal to $k_1 I_n \pm 2\%$			
	the pulse duration (s) corresponds to that indicated on the overload curve for $k_1 I_n$ stated by manufacturer			
	time (s) intervals between pulses equal to 30 times the pulse duration			
	fuse-links having ambient air temperature subjected to a current (A) equal to current for the overload test	12A		

IEC 60269-1					
Clause	Requirement + Test	Result - Remark			Verdict
	pre-arcing time (s) of sample lies within the manufacturers time-current zone :	34s	39s	40s	P
8.4.3.5	Conventional cable overload protection (for "gG" fuse-links only)	#13			
		In=63A			
	fuse-link mounted as specified in 8.4.1				P
	provided with PVC insulated copper conductors of cross-sectional area (mm ²) (see Table 19) :	50mm ² x1m			P
	fuse and conductor connected to it, preheated with rated current (A) of fuse-link :	125A			P
	for a time (h) equal to the conventional time.....:	2h			P
	test current increased to 1,45 I _z (A) (I _z specified in Table 19):	2432A			P
	the fuse-link operated in time (s) less than the conventional time (s):	1,80x10 ³ s			P
8.4.3.6	Operation of indicating devices and strikers, if any				
	Operation of indicating device verified in combination with the verification of breaking capacity (see 8.5.5)				N/A
	The verification of striker operation:				N/A
	"g" fuse-link tested at current (A) equal to current I ₄ (see Table 20 abd 21) :				N/A
	recovery voltage (V):				N/A
	stated recovery voltage (V) :				N/A
	"a" fuse-link tested at current (A) equal to current 2k ₁ I _n (A) (see Figure 2):				N/A
	recovery voltage (V):				N/A
	stated recovery voltage (V) :				N/A
	Striker operate during all tests made at recovery voltage of at least 20 V				N/A
	No failure of indicating device or striker				N/A
8.5	Verification of the breaking capacity				
8.5.1	The test arrangements as specified in 8.1.4				P
8.5.2	Characteristics of the test circuit as specified				
	Scheme of test circuit (see Figure 5)				P
	Deviations form specified characteristics of test circuit:				N/A
8.5.3	Measuring instruments				P
8.5.4	Calibration of test circuit				
	Calibration oscillograms and their evaluation				P
8.5.6	The breaking-capacity tests made at an ambient air temperature of (20 ± 5) °C	21°C			P
	Breaking-capacity tests on a.c. fuses				

IEC 60269-1					
Clause	Requirement + Test	Result - Remark			Verdict
8.5.5.1	Table 20, test No. 1 for "g" and "a" fuse-links	In=63A, Un=500V			
		#10	#11	#12	
	Rated breaking capacity of the fuse-links (kA), at voltage (V)	100kA / AC500V			
	Rated current (A) of the fuse-links	63A			P
	Prospective current I_1 (kA) equal to rated breaking capacity within a tolerance of + 10%, - 0%	120,4kA			P
	Power factor	0,17			P
	Initiation of arcing after voltage zero: within 40° - 65° for sample 1 and within 65° - 90° for sample 2 and 3,	61°	76°	76°	P
	for sample 1) arcing after voltage zero within 0° + 10°, - 0°				N/A
	Power-frequency recovery voltage: voltage (V) i.e (%) of rated voltage within 105% + 5%, - 0% of the rated voltage or 110% + 5%, - 0% of the rated voltage	568V			P
	Cut-off current (A)				P
8.5.8	Acceptability of No. 1 test results				
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	912V	949V	995V	P
	b) fuse-links operated without external effects or damage to the components of the complete fuse				P
	c) no permanent arcing, flashover or ejection of dangerous flames				P
	d) no damage of fuse components hindering from their further use				P
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier				P
	g) resistance (MΩ) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all other cases:				P
8.5.5.1	Table 20, test No. 2 for "g" and "a" fuse-links	In=63A, Un=500V			
		#7	#8	#9	
	Prospective current I_2 (kA)	12kA			P
	Test made under conditions which approximate those giving maximum arc energy				P
	Power factor	0,28			P
	Making angle after voltage zero: within tolerance 0° + 20°, - 0°	12,2°	11°	9,4°	P

IEC 60269-1					
Clause	Requirement + Test	Result - Remark			Verdict
	Power-frequency recovery voltage: voltage (V) i.e (%) of rated voltage within 105% + 5%, - 0% of the rated voltage or 110% + 5%, - 0% of the rated voltage	568V			P
	Recovery voltage maintained at a value (V); duration (s) for sample (No.)				N/A
	For other samples duration 15 s (8.5.5.2)				N/A
8.5.8	Acceptability of No. 2 test results				
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	1830V	1810V	1810V	P
	b) fuse-links operated without external effects or damage to the components of the complete fuse				P
	c) no permanent arcing, flashover or ejection of dangerous flames				P
	d) no damage of fuse components hindering from their further use				P
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier				P
	g) resistance (MΩ) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all othercases:				P
8.5.5.1	Table 20, test No. 2* for "g" and "a" fuse-links, for $I_2 \geq I_1$	(see appended table)			N/A
	Prospective current I_2 (kA) for test No. 2 greater than the rated breaking capacity (kA)				N/A
	Test made on six samples replacing tests of Nos.1 and 2. Test made with current I_1 (kA)				N/A
	Making angels differ approximately 30° between each test				N/A
	Power factor				N/A
8.5.8	Acceptability of No. 2 test results				
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)				N/A
	b) fuse-links operated without external effects or damage to the components of the complete fuse				N/A
	c) no permanent arcing, flashover or ejection of dangerous flames				N/A
	d) no damage of fuse components hindering from their further use				N/A
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				N/A

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict
	f) fuse-link remains in one pENe before its removal from the fuse- carrier		N/A
8.5.5.1	Table 20, test No. 3 for "g" and "a" fuse-links	In=63A, Un=500V	
		#6	
	Prospective current for "g" fuse-link I_3 (A) equal to $3,2 I_f$	819,2A	P
	Prospective current for "a" fuse-link I_3 (A) equal to $2,5 k_2 I_n$		N/A
	Power factor	0,41	P
	Tolerance on current $\pm 20\%$	978A	P
	Recovery voltage (V) maintained for 15 s(8.5.5.2)	568V	P
8.5.8	Acceptability of No. 3 test results		
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	872V	P
	b) fuse-links operated without external effects or damage to the components of the complete fuse		P
	c) no permanent arcing, flashover or ejection of dangerous flames		P
	d) no damage of fuse components hindering from their further use		P
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them		P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier		P
	g) resistance (M Ω) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all othercases:		P
8.5.5.1	Table 20, test No. 4 for "g" and "a" fuse-links	In=63A, Un=500V	
		#5	
	Prospective current for "g" fuse-link I_4 (A) equal to $2,0 I_f$	512A	P
	Prospective current for "a" fuse-link I_4 (A) equal to $1,6 k_2 I_n$		N/A
	Power factor	0,43	P
	Tolerance on current + 20%, - 0%	568A	P
	Recovery voltage (V) maintained for 15 s (8.5.5.2):	568V	P
8.5.8	Acceptability of No. 4 test results		
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	133V	P
	b) fuse-links operated without external effects or damage to the components of the complete fuse		P

IEC 60269-1					
Clause	Requirement + Test	Result - Remark			Verdict
	c) no permanent arcing, flashover or ejection of dangerous flames				P
	d) no damage of fuse components hindering from their further use				P
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier				P
	g) resistance (MΩ) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all othercases:				P
8.5.5.1	Table 20, test No. 5 for "g" and "a"fuse-links	In=63A, Un=500V			
		#4			
	Prospective current for "g" fuse-link I ₅ (A) equal to 1,25 I _f	320A			P
	Prospective current for "a" fuse-link I ₅ (A) equal to k ₂ I _n				N/A
	Power factor	0,47			P
	Tolerance on current + 20%, - 0%	382A			P
	Recovery voltage (V) maintained for 15 s (8.5.5.2):	568V			P
8.5.8	Acceptability of No. 5 test results				
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	162V			P
	b) fuse-links operated without external effects or damage to the components of the complete fuse				P
	c) no permanent arcing, flashover or ejection of dangerous flames				P
	d) no damage of fuse components hindering from their further use				P
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier				P
	g) resistance (MΩ) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all othercases:				P
	Breaking-capacity tests on a.c. fuses				
8.5.5.1	Table 20, test No. 1 for "g" and "a"fuse-links	In=63A, Un=500V			
		#113	#114	#115	
	Rated breaking capacity of the fuse-links (kA), at voltage (V)	50kA / AC500V			
	Rated current (A) of the fuse-links	63A			P

IEC 60269-1					
Clause	Requirement + Test	Result - Remark			Verdict
	Prospective current I_1 (kA) equal to rated breaking capacity within a tolerance of + 10%, - 0%	50,5kA			P
	Power factor	0,18			P
	Initiation of arcing after voltage zero: within 40° - 65° for sample 1 and within 65° - 90° for sample 2 and 3,	60°	79°	79°	P
	for sample 1) arcing after voltage zero within 0° + 10°, - 0°				N/A
	Power-frequency recovery voltage: voltage (V) i.e (%) of rated voltage within 105% + 5%, - 0% of the rated voltage or 110% + 5%, - 0% of the rated voltage	740V			P
	Cut-off current (A)				P
8.5.8	Acceptability of No. 1 test results				
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	1010V	1030V	1030V	P
	b) fuse-links operated without external effects or damage to the components of the complete fuse				P
	c) no permanent arcing, flashover or ejection of dangerous flames				P
	d) no damage of fuse components hindering from their further use				P
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier				P
	g) resistance (MΩ) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all othercases:				P
8.5.5.1	Table 20, test No. 2 for "g" and "a" fuse-links	In=63A, Un=500V			
		#110	#111	#112	
	Prospective current I_2 (kA)	12kA			P
	Test made under conditions which approximate those giving maximum arc energy				P
	Power factor	0,29			P
	Making angle after voltage zero: within tolerance 0° + 20°, - 0°	6,2°	7,1°	5,8°	P
	Power-frequency recovery voltage: voltage (V) i.e (%) of rated voltage within 105% + 5%, - 0% of the rated voltage or 110% + 5%, - 0% of the rated voltage	740V			P
	Recovery voltage maintained at a value (V); duration (s) for sample (No.)				N/A
	For other samples duration 15 s (8.5.5.2)				N/A

IEC 60269-1					
Clause	Requirement + Test	Result - Remark			Verdict
8.5.8	Acceptability of No. 2 test results				
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	1810V	2310V	2420V	P
	b) fuse-links operated without external effects or damage to the components of the complete fuse				P
	c) no permanent arcing, flashover or ejection of dangerous flames				P
	d) no damage of fuse components hindering from their further use				P
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier				P
	g) resistance (MΩ) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all othercases:				P
	Breaking-capacity tests on a.c. fuses				
8.5.5.1	Table 20, test No. 1 for "g" and "a"fuse-links	In=32A, Un=500V			
		#33	#34	#35	
	Rated breaking capacity of the fuse-links (kA), at voltage (V)	100kA / AC500V			
	Rated current (A) of the fuse-links	32A			P
	Prospective current I ₁ (kA) equal to rated breaking capacity within a tolerance of + 10%, - 0%	120,4kA			P
	Power factor	0,17			P
	Initiation of arcing after voltage zero: within 40° - 65°for sample 1 and within 65° - 90° for sample 2 and 3,	54°	72°	70°	P
	for sample 1) arcing after voltage zero within 0° + 10°, - 0°				N/A
	Power-frequency recovery voltage: voltage (V) i.e (%) of rated voltage within 105% + 5%, - 0% of the rated voltage or 110% + 5%, - 0% of the rated voltage	568V			P
	Cut-off current (A)				P
8.5.8	Acceptability of No. 1 test results				
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	788V	808V	799V	P
	b) fuse-links operated without external effects or damage to the components of the complete fuse				P
	c) no permanent arcing, flashover or ejection of dangerous flames				P
	d) no damage of fuse components hindering from their further use				P

IEC 60269-1					
Clause	Requirement + Test	Result - Remark			Verdict
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier				P
	g) resistance (MΩ) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all othercases:				P
	Breaking-capacity tests on a.c. fuses				
8.5.5.1	Table 20, test No. 1 for "g" and "a"fuse-links	In=32A, Un=500V			
		#116	#117	#118	
	Rated breaking capacity of the fuse-links (kA), at voltage (V)	50kA / AC500V			
	Rated current (A) of the fuse-links	32A			P
	Prospective current I ₁ (kA) equal to rated breaking capacity within a tolerance of + 10%, - 0%	50,5kA			P
	Power factor	0,18			P
	Initiation of arcing after voltage zero: within 40° - 65°for sample 1 and within 65° - 90° for sample 2 and 3,	64°	78°	78°	P
	for sample 1) arcing after voltage zero within 0° + 10°, - 0°				N/A
	Power-frequency recovery voltage: voltage (V) i.e (%) of rated voltage within 105% + 5%, - 0% of the rated voltage or 110% + 5%, - 0% of the rated voltage	740V			P
	Cut-off current (A)				P
8.5.8	Acceptability of No. 1 test results				
	a) max. arc voltage (V) did not exceed stated values of 7.5 (Table 6)	1040V	1110V	1130V	P
	b) fuse-links operated without external effects or damage to the components of the complete fuse				P
	c) no permanent arcing, flashover or ejection of dangerous flames				P
	d) no damage of fuse components hindering from their further use				P
	e) no damage of fuse-link such, that it is difficult or dangerous to replace them				P
	f) fuse-link remains in one pENe before its removal from the fuse- carrier				P
	g) resistance (MΩ) between contacts of fuse-links after test not less than 50 000 Ω for the rated voltage of fuse-links to 250 V, 100 000 Ω in all othercases:				P
	Breaking-capacity tests on d.c. fuses				
8.6	Verification of the cut-off current characteristics				

IEC 60269-1					
Clause	Requirement + Test	Result - Remark			Verdict
8.6.2	The values measured did not exceed cut-off characteristics indicated by the manufacturer (see 5.8.1)				P
8.7	Verification of I ² t characteristics and overcurrent discrimination	In=63A	In=32A		
		#21~24(fuse)	#43~46(fuse)		
8.7.2	The operating I ² t values measured not exceed the values indicated by the manufacturer, or				N/A
	those specified in subsequent parts	Part 2 (IEC 60269-2)			P
	The pre-arcing I ² t values not less than minimum pre-arcing values given by the manufacturer, or				N/A
	they lie within the limits indicated in Table 7				P
8.7.3	Verification of compliance for fuse-links at 0,01 s				
	"gG" and "gM" fuse-links at 0,01 s comply with Table 7				P
8.7.4	Verification of overcurrent discrimination				
	The discrimination of the fuse-links verified by means of the time-current characteristics and the pre-arcing and operating I ² t values	Part 2 (IEC 60269-2)			N/A
8.8	Verification of the degree of protection of enclosures				
	Degree of protection IP:	IP			N/A
	Verification by test under conditions specified in EN 60529:				N/A
8.9	Verification of resistance to heat	#2 (fuse-base)	#10(fuse)		
	No damage impaired by heat during the previous tests (in particular with respect to 8.3, 8.4, 8.5 and 8.10)				P
8.10	Verification of non-deterioration of contacts				
8.10.1	Three samples provided with standardized dummy fuse-links of the highest current rating (A) intended to be used in the fuse-holder (see subsequent parts):	Part 2 (IEC 60269-2)			P
8.10.2	Test current (A) for load period:				N/A
	Duration (s) of load period :				N/A
	Duration (s) of no-load period :				N/A
	a) Test of 250 cycles, measured values not exceed the limits given in subsequent parts				N/A
	b) Test of 750 cycles, measured values not exceed the limits given in subsequent parts				N/A
8.11	Mechanical and miscellaneous tests				
8.11.1	Mechanical strength	#6	#7	#8	
		Fuse-base			

IEC 60269-1				
Clause	Requirement + Test	Result - Remark		Verdict
	Mechanical characteristics of fuse and its parts judged in the context of normal handling and mounting as well as with results shown after breaking-capacity test (see 8.5), if not otherwise specified in the subsequent parts			P
8.11.2	Miscellaneous tests			
8.11.2.1	Verification of freedom from season cracking			
	Current-carrying parts made of rolled copper alloy with less than 83% copper content and with all grease removed, placed for 4 h in test cabinet having temperature of (30 ± 10) °C			P
	After this, samples placed for 8 h in test cabinet, on the bottom of which is ammonium chloride solution having pH value 10 - 11			P
	After test no cracks visible to the unaidedeye			P
8.11.2.2	Verification of resistance to abnormal heat and fire			
8.11.2.2.1	Parts of insulating material, except ceramic, have a limited duration of burning without spreading fire by flames or burning droplets or glowing particles falling from the specimen			P
8.11.2.2.5	Glow-wire test: (650 ± 10) °C			
	Parts of insulating materials not necessary to retain current-carrying parts in position even though they are in contact with them, made the glow-wire test (650 ± 10) °C			N/A
	No visible flame, or burning or glowing of the specimen extinguish within max. (s) after removal of the glow-wire. Limit (30 ± 1) s :			N/A
	No burning of the tissue paper			N/A
	No scorching of the pinewood board			N/A
	Glow-wire test: (960 ± 10) °C			
	Parts of insulating materials necessary to retain current-carrying parts and parts of the earthing circuit, if any, in position , made the glow-wiretest (960 ± 10) °C			P
	No visible flame, or burning or glowing of the specimen extinguish within max. (s) after removal of the glow-wire. Limit (30 ± 1) s :			P
	No burning of the tissue paper			P
	No scorching of the pinewood board			p
8.11.2.3	Verification of resistance to rusting	#131(fuse)	#2(fuse-base)	
	Tested parts after degreasing (10 min in specified solution) placed for 10 min in air saturated with moisture and after that dried 10 min in an ambient temperature (100 ± 5) °C			P

IEC 60269-1			
Clause	Requirement + Test	Result - Remark	Verdict

	Surface of tested parts show no signs of rust		P
--	---	--	---

8.1.5.1

[illegible]

8.4.3.1	TABLE: Verification of conventional non-fusing and fusing current						
a) the fuse-link subjected to the conventional non-fusing current (I_{nf})							
ambient air temperature: 24°C							
Sample No.:	#1	#32					
I_n (A):	63A	32A					
I_{nf} (A):	200A	6A					
T_{nf} (h):	>2h	>1h					
Sample No.:	#74	#79					
I_n (A):	40A	32A					
I_{nf} (A):	50A	40A					
T_{nf} (h):	>1h	>1h					
b) the same fuse-link, after cooled down to ambient temperature, subjected to the conventional fusing current (I_f)							
ambient air temperature: 24°C							
Sample No.:	#1	#32					
I_n (A):	63A	32A					
I_f (A):	256A	8,32A					
T_f (s):	1h3min19s	11min22s					

8.4.3.2	TABLE: Verification of rated current of “g” fuse-links						
ambient air temperature: 24°C							
Sample No.:	#2	#57					
I _n (A):	63A	32A					
Test current (A)	168A	832A					
conventional time (h)	2h	2h					
0,1 of the conventional time(min)	12min	12min					
8.4.3.1a) the fuse-link subjected to the conventional non-fusing current (I _{nf})							
I _n (A):	63A	32A					
I _{nf} (A):	200A	100A					
T _{nf} (h):	>2h	>2h					
Sample No.:	#74	#95					
I _n (A):	40A	16A					
Test current (A)	42A	16,8A					
conventional time (h)	1h	1h					
0,1 of the conventional time(min)	6min	6min					

8.4.3.3.2	TABLE: Verification of gates			
I_n (A):	63A			
Sample No.:	#17	#18	#19	#20
	Time of Operation			
I_{min} (10s):	460A	>10s		
I_{max} (5s):	950A	4,1s		
I_{min} (0,1s):	1450A		>0,1s	
I_{max} (0,1s):	2590A			52ms
I_n (A):	32A			
Sample No.:	#58	#59	#60	#61
	Time of Operation			

8.4.3.3.2	TABLE: Verification of gates			
I _{min} (10s): 215A	>10s			
I _{max} (5s): 425A		4,5s		
I _{min} (0,1s): 610A			>0,1s	
I _{max} (0,1s): 1100A				64ms

Photo of the sample

